



# SB72-301CR PHY Patch

**NetBurner Part Number: SB72-301CR**

**Description: New Ethernet driver for Ethernet PHY component**

**Software Required: NNDK 1.99 Final**

**Implementation Date: January 26, 2012**

**NOTE: If your application was built with NNDK 2.5.2 or later, do not use the patch. Your software already has support for the new Ethernet PHY.**

## Step one:

Verify that your NNDK release version is 1.99 by opening the release tag file located here:  
C:\nburn\release\_tag


## Step two:

Download the “SB72\_NNDK199\_Micrel\_Ethernet\_Patch.zip” from the NetBurner website.

NOTE: Contact NetBurner Sales at [sales@netburner.com](mailto:sales@netburner.com) and request the “SB72 NNDK199 Micrel Ethernet Patch”.


## Step three:

Unzip the “SB72\_NNDK199\_Micrel\_Ethernet\_Patch.zip” file and then copy and paste the entire directory over the c:\nburn directory. You should receive a message such as the following:




## Step four:

Open NetBurner Eclipse and Rebuild All System Files. The dropdown menu should look like this:



You should receive a message such as the following:



## Step five:

Recompile your application. The NetBurner software will automatically recognize the type of PHY used, so new code images can be used for both the SB72-300CR (AMD PHY) and SB72-301CR (Micrel PHY) hardware assemblies.

If you have any questions please contact our sales team at [sales@netburner.com](mailto:sales@netburner.com).

Sincerely,

NetBurner Customer Service